

CJX2 AC Contactor

JRS1, JR28 Thermal Relay

Type		Rated frame current of thermal relay	Rated current (A)	Current setting range(A)
JRS1-25 (LR1-D25322)		25	0.16	0.1~0.16
			0.25	0.16~0.25
			0.40	0.25~0.40
			0.63	0.40~0.63
			1	0.63~1
			1.6	1~1.6
			2.5	1.6~2.5
			4	2.5~4
			6	4~6
			8	5.5~8
			10	7~10
			13	10~13
			18	13~18
			25	18~25
JRS1-80 (LR1-D80363)		80	32	23~32
			40	30~40
			50	38~50
			57	48~57
			66	57~66
			80	63~80
JR28-25 (LR2-D13)		25	0.16	0.10-0.16
			0.25	0.16-0.25
			0.40	0.25-0.40
			0.63	0.40-0.63
			1.0	0.63-1.0
			1.6	1.0-1.6
			2.0	1.25-2.0
			2.5	1.6-2.5
			4.0	2.5-4.0
			6.0	4.0-6.0
			8.0	5.5-8.0
			10.0	7.0-10.0
			13.0	9.0-13.0
			18.0	12.0-18.0
JR28-36 (LR2-D23)		36	25.0	17.0-25.0
			32	23.0-32
JR28-93 (LR2-D33)		93	36	28.0-36
			32	23.0-32.0
			40	30.0-40.0
			50	37.0-50.0
			65	48.0-65.0
			70	55.0-70.0
			80	63.0-80.0
			93	80.0-93.0