

QS5 Cam Starter



1. General

QS5 cam starter is mainly used to start, stop, forward or backward directly three-phase asynchronous electric motor with AC 50Hz, voltage up to 500V and capacity up to 7.5kW. It can also be used for changeover from one kind of circuit to the other .

2. Specifications

Type	Mark	Rated current (A)	Motor control capacity (HP)	Electrical life (times)	Mechanical life (times)	Frequency of operation (per hr)	Applications	Position of lever
QS5-15A	-○	15	5.5	100000	250000	200	ON-OFF switching	0-60
QS5-30A		30	10					
QS5-15N	-○-	15	5.5				Formard & reverse	60-0-60
QS5-30N		30	10					
QS5-15P/3	-○-	15	5.5				For 3 pole two circuits	60-0-60
QS5-30P/3		30	10					
QS5-63A	-○	63	22	8000	200000	180	ON-OFF switching	0-60
QS5-100A		100	30					
QS5-63N	-○	63	22				Formard & reverse	60-0-60
QS5-100N		100	30					
QS5-63P/4	-○-	63	22				For 3 pole two circuits	60-0-60
QS5-100P/4		100	30					