

## **BK2 Control Transformer**



### 1. General


This series control and lighting purposed miniature dry type air automatic mode transformer (hereinafter referred to as transformer) is suitable for circuit of AC 50/60Hz and rated voltage 500V and below, it can be used as control power supply for general electrical appliances such as various machine tools and mechanical equipment, it also can be used as power supply for illuminating lamps.

This series of transformer adopts advanced technology and strict design, with practical and latemodel structure, (patent No.: ZL 200620115517.6), with advantages of excellent performance, reliable operation, wide application, etc furthermore, it can work for long term under rated load condition, it really is an ideal voltage transformation power supply.

# 2. Type designation




## 3. Overall and mounting dimensions(mm)





# **BK2 Control Transformer**



Rated capacity (VA)	Primary voltage (V)	Secondary voltage (V)	Outline size (mm)			Mounting size (mm)	
			B max	D max	H max	А	С
25/50			80/85	70/71	89/94	56	51
100			103	83	110	76	51
150			103	91	110	76	64
200		6.3, 12, 24,	103	103	110	76	74
250	220	36, 110,	121	108	126	90	78
300		000000 000000	121	113	126	90	83
400	380	127, 220,	151	100	152	110	76
500	Or be	380	151	110	152	110	82
700	customized	Or be	151	144	152	110	107
1000	Customized		151	170	152	110	107
1500		customized	240	190	240	130	110
2000			240	210	240	130	120
2500			240	250	245	130	150
3000			240	250	245	130	150
4000			320	240	360	200	125
5000			320	240	360	200	125